

# Roger™ design-integrated receivers (03)

Product information and technical data



**roger**

Roger design-integrated receivers are compatible with most Phonak hearing instruments. Simply use this guide to choose the correct Roger receiver for the Phonak hearing instrument in question.

For more information visit [www.phonakpro.com](http://www.phonakpro.com)

# What is Roger

Roger is the digital standard that bridges the understanding gap, in noise and over distance, by wirelessly transmitting the speaker's voice directly to the listener.

## Key features

### Additional adaptive gain

Roger receivers automatically adjust the output gain according to the surrounding noise level to maintain intelligibility in noisy environments. The noise level is measured by the Roger microphone and sent to the Roger receiver along with the audio signal.

### Effective stand-by mode

Roger receivers automatically enter stand-by mode if the connected microphone is turned off or moves out of range. In stand-by mode power usage is reduced to increase the battery's life.

## Phonak hearing instrument compatibility



Roger™ 19	Roger™ 18	Roger™ 16*	Roger™ 15*	Roger™ 13*	Roger™ 11*	Roger™ 10*
Phonak Naida™ B-UP	Phonak Audéo™ B-13	Phonak Bolero™ Q-P	Phonak Sky™ Q-RIC	Phonak Ambra microP	Phonak Sky™ Q-SP	Phonak Sky™ Q-UP
Phonak Sky™ B-UP	Phonak Bolero™ B-P	Phonak Bolero™ Q-SP	Phonak Sky™ Q-M13	Phonak Ambra SP	Phonak Naida™ Q-SP	Phonak Naida™ Q-UP
Phonak Vitus™ UP	Phonak Bolero™ B-SP		Phonak Naida™ Q-RIC	Phonak Solana microP	Phonak Naida™ S SP	Phonak Naida™ S UP
Phonak Vitus+™ UP	Phonak Naida™ B-SP		Phonak Naida™ S CRT	Phonak Solana SP	Phonak Naida™ SP	Phonak Naida™ UP
Phonak Naida™ V-UP	Phonak Sky™ B-RIC		Phonak Bolero™ Q-M13	Phonak Cassia microP		Phonak Naida™ Link UP
Phonak Sky™ V-UP	Phonak Sky™ B-P		Phonak Ambra M H20	Phonak Cassia SP		
	Phonak Sky™ B-SP		Phonak Solana M H20	Phonak Dalia microP		
	Phonak Vitus™ P		Phonak Dalia M H20	Phonak Dalia SP		
	Phonak Vitus+™ RIC		Phonak Cassia M H20			
	Phonak Vitus+™ P		Phonak Nios S H20			
	Phonak Audéo™ V-13		Phonak Naida™ Link RIC			
	Phonak Bolero™ V-P					
	Phonak Bolero™ V-SP					
	Phonak Naida™ V-SP					
	Phonak Sky™ V-RIC					
	Phonak Sky™ V-P					
	Phonak Sky™ V-SP					

Note: to check the compatibility of new Phonak hearing instruments visit [www.phonakpro.com](http://www.phonakpro.com)  
 \* No longer available

## Housing colors



Roger™ 19

Roger™ 18

P1	Sand Beige	•	•
P5	Champagne	•	•
P6	Silver Gray	•	•
P7	Graphite Gray	•	•
P8	Velvet Black	•	•
O3	Caribbean Pirate	•	•
T3	Precious Pink	•	•
M6	Lava Red	•	•
M7	Blue Ocean	•	•
M8	Majesty Purple	•	•

## Options

	Roger™ 19	Roger™ 18
Tamperproof housing kit for babies and toddlers (0 – 36 month)	•	•

## General data

Type:	Roger receiver Operates with Roger Select™, Roger™ Table Mic II, Roger Pen™, Roger™ EasyPen and Roger™ Clip-On Mic
Operating conditions:	The product has been designed for trouble-free operation without restrictions when used as intended, unless otherwise stated in the user guide 0°C to +60°Celsius / +32°F to +140°Fahrenheit and relative humidity <95% (non condensing)
Transport and storage conditions:	-20°C to +60°Celsius / -4°F to +140°Fahrenheit and relative humidity of <70% for a long period of time

## Audio characteristics

Audio bandwidth:	100 Hz – 7.2 kHz
Distortion:	< 2% for fmod = 1 kHz
Audio signal output:	-54 dBV (transmitter in compression, fmod = 1 kHz, Surrounding noise level < 58 dB SPL)
Additional adaptive audio gain:	Up to 20 dB

## Size and Weight



	Roger™ 19	Roger™ 18	Roger™ 16	Roger™ 15	Roger™ 13	Roger™ 11	Roger™ 10
Height (connected to HI):	8.5 mm / 0.335 inch	8.1 mm / 0.319 inch	8.4 mm / 0.330 inch	8.5 mm / 0.335 inch	11 mm / 0.433 inch	8 mm / 0.315 inch	20 mm / 0.787 inch
Length:	14 mm / 0.551 inch	12.4 mm / 0.488 inch	11.8 mm / 0.465 inch	12.4 mm / 0.488 inch	11 mm / 0.433 inch	12 mm / 0.472 inch	15 mm / 0.591 inch
Width:	7.5 mm / 0.295 inch	7.6 mm / 0.299 inch	7.2 mm / 0.283 inch	8 mm / 0.315 inch	9 mm / 0.354 inch	9 mm / 0.354 inch	9 mm / 0.354 inch
Weight:	0.9 g / 0.0022 lb	0.9 g / 0.0022 lb	0.9 g / 0.0022 lb	0.9 g / 0.0022 lb	1.1 g / 0.0022 lb	1.0 g / 0.0022 lb	1.1 g / 0.0022 lb

<sup>1</sup> IP68 indicates that when connected to a compatible hearing instrument the Roger receiver was not damaged beyond repair after 8 hours in a dust chamber, nor after being immersed in 1 meter (3 feet) of water for 60 minutes as defined by IEC60529.

## Roger characteristics

Frequency:	2.4 GHz ISM Band
Transmission delay:	< 20 ms
Antenna:	Built-in ear level antenna
Backlink RF power:	0.02 mW

## Power management

Power supply:	Supplied by the HI battery
Voltage range:	1.0 to 1.5 V
Current drain*:	Active mode: 2.7 mA for V <sub>BAT</sub> = 1.2 V Stand-by: 0.5 mA for V <sub>BAT</sub> = 1.2 V

## Standards

Radiocom:	EN 300 440 FCC part 15.249
EMC:	EN 60601-1-2, EN 301 489 FCC part 15b
Water Resistant:	IP68 <sup>1</sup> for Roger™ 19, Roger™ 18