

Roger™ Focus II.

Product information

Roger Focus II is a Roger receiver designed to empower individuals with Unilateral Hearing Loss (UHL), Auditory Processing Disorder (APD), and Autism Spectrum Disorder (ASD) to hear clearly and concentrate whether in learning environments or outside.

Powered by the Roger technology, it reduces the effects of distance, background noise and reverberation.



Product description



Roger Focus II-312



Roger Focus II

Battery size		312 (tamperproof kit available)	built-in rechargeable
Multi-function button		•	•
Multi-function button volume adjustment		-8 dB <-> +8 dB (2 dB step)	-8 dB <-> +8 dB (2 dB step)
Indicator light		•	•
Colors		2	10
Nano coating		•	•
IP rating		IP68 ¹	IP68 ¹
Dimensions	L x W x D	31.3 x 14.1 x 7.3 (1.23 x 0.56 x 0.29")	36.7 x 16.4 x 8.5 (1.44 x 0.65 x 0.33")
	Weight	2.18 g / 0.077 oz	3.71 g / 0.131 oz
Charging times ²	0% to 100%		3 h
	0% to 80%		1.5 h
		SlimTube HE	SlimTube HE
Max. Power Output		90 dBA freefield equivalent	90 dBA freefield equivalent
Frequency range (Hz)		<100 - >7000	<100 - >7000
Working current (mA)		1.5	1.5

Roger characteristics

Frequency	2.4 GHz including adaptive automatic frequency hopping
Antenna	built-in antenna
Backlink RF power	< 0.02 mW

Housing colors

Roger Focus II



Q2

Electric Green



Q3

Caribbean
Pirate



T3

Precious Pink



M6

Lava Red



M7

Blue Ocean



M8

Majesty Purple



P6

Silver Gray



P8

Velvet Black



H0

Beige

Roger Focus II-312



P6

Silver Gray



P8

Velvet Black

¹ IP68 indicates that the hearing device is water and dust resistant. It survived continuous immersion in 1 meter of fresh water for 60 minutes and 8 hours in a dust chamber as per the IEC60529 standard.
² Actual charging time depends on the remaining battery life and may be affected by temperature conditions.

Acoustic coupling

Sound outlet	SlimTube HE	Available in left, right and five different lengths (00, 0, 1, 2, 3)
Earpiece for SlimTube	Dome	Open dome (three sizes: S, M, L), Cap dome (one size)

Wireless communication portfolio

Roger	Roger Focus II-312	Roger Focus II
Roger microphones	•	•

Fitting

Roger Focus II is solely a Roger receiver. No fitting required. Firmware updates to Roger Focus II can be done via Phonak Target using Noahlink wireless.

Roger Focus II charging options

Phonak Charger BTE RIC and Phonak Charger Combi BTE 2 are suitable for Roger Focus II.



Phonak RemoteControl

The Phonak RemoteControl is suitable for Roger Focus II. It allows volume adjustments and locks the volume button.



life is on

Since 1947, Phonak is dedicated to preserving life quality by opening new acoustic worlds. Already back then, in the days of our foundation, our company was driven by a formative conviction: We believe that well-hearing equates to well-being and thus is essential for living life to the fullest. In fact, the sense of hearing is directly linked to social, emotional, cognitive and physical well-being. Today as in future, we thrive to offer the broadest portfolio of innovative hearing solutions. And, together with our hearing care professionals, we keep on focusing on what matters most: improving speech understanding, changing people's lives and having a positive effect on society as a whole.

phonak.com/focus



027-0601-02/V2.00/2026-01/jb © 2026 Sonova AG. All rights reserved.

