

Phonak Audéo™ L.

Product information

Phonak Audéo L is the comprehensive RIC portfolio for mild to profound hearing losses. Phonak Audéo L includes four designs, four performance levels and five external receivers, including the ActiveVent™ receiver.

Powered by the innovative technology of the Phonak Lumity platform, Phonak Audéo L hearing aids are the solution for those clients that prefer flexible and discreet RIC housings



Product description









| Audéo L-R | | | | |
|-----------------|--|--|--|--|
| Audéo L-R Trial | | | | |
| 100/170/150/100 | | | | |

Audéo L-312

| | | Audéo L-R Audéo L-R Trial L90/L70/L50/L30 | Audéo L-RT Audéo L-RT Trial L90/L70/L50/L30 | Audéo L–RL Audéo L–RL Trial L90/L70/L50/L30 | Audéo L-312 Audéo L-312 Trial L90/L70/L50/L30 |
|-------------------------------|-----------------|---|---|---|---|
| Battery size | | built-in rechargeable | built-in rechargeable | built-in rechargeable | 312 |
| Multi-function button | | • | • | • | • |
| Telecoil | | | • | | |
| Bluetooth® | | • | • | • | • |
| Hydrophobic coating | | • | • | • | • |
| IP rating | | IP681 | IP681 | IP681 | IP681 |
| Dimensions | L x W x D | 27.7 x 12 x 8.1 mm (1.09 x 0.47 x 0.32") | 30.3 x 12.6 x 8.1 mm (1.19 x 0.5 x 0.32") | 29.5 x 12.9 x 9 mm (1.16 x 0.51 x 0.35") | 26.8 x 11.2 x 7.1 mm (1.05 x 0.44 x 0.28") |
| | Weight | 2.2 g (0.08 oz) | 2.6 g (0.09 oz) | 2.8 g (0.1 oz) | 1.1 g (0.04t oz) |
| Charging times ² | 0% to 100% | 3 h | 3 h | 3 h | |
| | 0% to 80% | 1.5 h | 1.5 h | 2.0 h | |
| | 30 min. fitting | 15 min. | 15 min. | 20 min. | |
| S Receiver 4.0 | | | | | |
| Max. Power Output (dB SPL) | 2 cc coupler | 111 | 111 | 111 | 111 |
| Max. gain (dB) | 2 cc coupler | 47 | 47 | 47 | 47 |
| Frequency range (Hz) | | <100 - >8000 | <100 - >8000 | <100 - >8000 | <100 - >8000 |
| M Receiver 4.0 | | | | | |
| Maximum Power Output (dB SPL) | 2 cc coupler | 114 | 114 | 114 | 114 |
| Max. gain (dB) | 2 cc coupler | 51 | 51 | 51 | 51 |
| Frequency range (Hz) | | <100 - >8000 | <100 - >8000 | <100 - >8000 | <100 - >8000 |
| MAV Receiver | | | | | |
| Maximum Power Output (dB SPL) | 2 cc coupler | 119 | 119 | 119 | |
| Max. gain (dB) | 2 cc coupler | 50 | 50 | 50 | |
| Frequency range (Hz) | | <100 - >8000 | <100 - >8000 | <100 - >8000 | |
| P Receiver 4.0 | | | | | |
| Maximum Power Output (dB SPL) | 2 cc coupler | 122 | 122 | 122 | 122 |
| Max. gain (dB) | 2 cc coupler | 59 | 59 | 59 | 59 |
| Frequency range (Hz) | | <100 - 6300 | <100 - 6300 | <100 - 6300 | <100 - 6300 |
| UP Receiver | | | | | |
| Max. Power Output (dB SPL) | 2 cc coupler | 132 | 132 | 132 | 132 |
| Max. gain (dB) | 2 cc coupler | 71 | 71 | 71 | 71 |
| Frequency range (Hz) | | <100 - 6100 | <100 - 6100 | <100 - 6100 | <100 - 6100 |
| | | | | | |

Housing colors

















Gray



Gray













Precious

¹ IP68 indicates that the hearing aid is water and dust resistant. It survived continuous immersion in 1 meter of fresh water for 60 minutes and 8 hours in a dust chamber as per the IEC60529 standard.

Performance levels

| AutoSense OS™ 5.0 | Premium | Advanced | Standard | Essential |
|--------------------------|---------|----------|----------|-----------|
| Comfort in Echo | • | | | |
| Speech in Car | • | | | |
| Speech in Loud Noise | • | | | |
| Music | • | • | | |
| Comfort in Noise | • | • | • | |
| Speech in Noise | • | • | • | • |
| Calm Situation | • | • | • | • |
| Media speech + mic | • | • | • | • |
| Media music + mic | • | • | • | • |
| Additional programs | | | | |
| Max. additional programs | 4 | 4 | 4 | 4 |
| Comfort in Echo | • | | | |
| Speech in Loud Noise | • | • | | |
| Speech in 360° | • | • | | |
| Speech in Noise | • | • | • | • |
| Calm Situation | • | • | • | • |
| Comfort in Noise | • | • | • | • |
| Music | • | • | • | • |
| Acoustic phone | • | • | • | • |
| Custom program | • | • | • | • |
| Streaming programs | | | | |
| RogerDirect + mic | • | • | • | • |
| PartnerMic + mic | • | • | • | • |
| Phone call + mic | • | • | • | • |

| Features | Premium | Advanced | Standard | Essential |
|--|---------|----------|----------|-----------|
| SpeechSensor | • | | | |
| Speech Enhancer StereoZoom 2.0 | • | | | |
| StereoZoom 2.0 | • | • | | |
| | • | • | | |
| Dynamic Noise Cancellation Motion Sensor Hearing ¹ | • | • | • | |
| RogerDirect™ | • | • | • | • |
| ActiveVent™1 | • | • | • | • |
| UltraZoom | • | • | • | • |
| EchoBlock | • | | | |
| Tap control ¹ | | | | |
| - Siri/Google Assistant | • | • | | |
| - Pause/resume streaming | • | • | | |
| - Accept/end phone call | • | • | | |
| SoundRelax | • | • | | |
| DuoPhone | • | • | • | |
| Real Ear Sound | • | • | • | |
| Health functionalities1,2 | • | • | • | • |
| WindBlock | • | • | • | • |
| User Preference Tuning | • | • | • | • |
| Tinnitus Balance | • | • | • | • |
| Auto Acclimatization | • | • | • | • |
| Environmental balance | • | • | • | • |
| SoundRecover2 | • | • | • | • |
| WhistleBlock | • | • | • | • |
| NoiseBlock | • | • | • | • |
| QuickSync | • | • | • | • |
| AOV | • | • | • | • |
| Fine tuning channel | 20 | 20 | 16 | 12 |

Fitting

| | Audéo L-R Audéo L-R Trial | Audéo L-RT Audéo L-RT Trial | Audéo L-RL Audéo L-RL Trial | Audéo L-312 Audéo L-312 Trial |
|--|------------------------------|--------------------------------|--------------------------------|----------------------------------|
| Phonak Target | 8.0 or higher | 8.0 or higher | 8.0 or higher | 9.1 or higher |
| Noahlink Wireless, Noahlink Wireless 2 | • | • | • | • |

¹ Available for rechargeable models only 2 Available in combination with myPhonak

Acoustic coupling

| Length | S Receiver | M Receiver | MAV Receiver ¹ | P Receiver | UP Receiver |
|--|--|------------|---|------------|---|
| Available in four different lengths (0, 1, 2, 3), left and right | • | • | • | • | • |
| Dome | | | | | |
| Cap dome | • | • | | • | |
| Open dome Available in three sizes (S, M, L) | • | • | | • | |
| Vented dome Available in three sizes (S, M, L) | • | • | | • | |
| Power dome Available in three sizes (S, M, L) | • | • | | • | |
| SlimTip ² | | | | | |
| Acryl | • | • | | • | |
| Silicone | • | • | | • | |
| Titanium AV | | | • | | |
| Universal AV Available in four shapes (A, B, C, D) | | | • | | |
| cShell | | | | | |
| Acryl | • | • | | • | • |
| Titanium | • | • | | • | • |
| Fitting ranges | | | | | _ |
| 1 Combination not available with Audéo L-312 2 Available with extra canal length option | d8 HL 10 10 20 50 40 40 40 40 100 1100 1100 1100 1100 | | 0 10 20 30 40 40 40 40 40 40 40 40 40 40 40 40 40 | | dB HL 0 10 20 30 40 40 50 60 70 80 90 100 100 100 100 100 Moderate to profound hearing loss. |

Phonak SmartSpeech™ Technology

SmartSpeech Technology represents our dedication to designing features that improve speech understanding and reduce listening effort in various listening environments³. Our heritage of features include Speech Enhancer, Dynamic Noise Cancellation and Motion Sensor Hearing. With Phonak Audéo Lumity we introduce two new features: StereoZoom 2.0 and SpeechSensor in addition to the existing benefits of ActiveVent Receiver and RogerDirect Technology.

Phonak Audéo L Trial

The Phonak Audéo L Trial hearing aids can be quickly set to the desired performance level in order to suit your recommendation. All levels of technology in one Phonak Audéo L Trial hearing aid provides you with many options for providing the hearing solution at the first appointment or bridging the gap during repairs.

Latzel, M., Lesimple, C., & Woodward, J. (2023) Speech Enhancer significantly reduces listening effort and increases intelligibility for speech from a distance. Phonak Field Study News. www.phonak.com/evidence

³ Appleton, J. (2020) AutoSense OS 4.0 - significantly less listening effort and preferred for speech intelligibility. Phonak Field Study News. www.phonak.com/evidence Latzel, M. & Hobi, S. (2022) ActiveVent™ Receiver provides benefit of open and closed acoustics for better speech understanding in noise and naturalness of own voice perception. Phonak Field Study News. www.phonak.com/evidence

Thibodeau L.M. (2020) Benefits in Speech Recognition in Noise with Remote Wireless Microphones in Group Settings. Journal of the American Academy of Audiology, 31(6), 404–411

Phonak Audéo L charging options



Phonak Charger Ease and Charger Ease Go

The Phonak Charger Ease is a compact charger with magnets in the charging slots that make it easy to insert and remove Audéo L-R and RT. Phonak Charger Ease Go in addition features a built-in battery that can charge two hearing aids three times. Both chargers have a standard USB-C charging port that lights up when power is applied.



Phonak Charger Case Go and Phonak Life Charger

There are two options available for Audéo L-RL. Phonak Charger Case Go features a built-in battery that can charge two hearing aids three times. Both chargers have a standard USB-C charging port that lights up when power is applied.

Phonak Audéo L Bluetooth® versions

Direct calls/audio streaming

Bluetooth 4.2 wireless technology and most older Bluetooth phones

Wireless communication portfolio

| L90/L70/L50/L30 | Audéo L-RT Trial | Audéo L–RL Trial L90/L70/L50/L30 | Audéo L-312 Trial L90/L70/L50/L30 |
|-----------------|------------------------------------|-------------------------------------|--|
| | | | |
| • | • | • | • |
| • | • | • | • |
| • | • | • | • |
| | | | |
| • | • | • | • |
| | | | |
| • | • | • | • |
| • | • | • | • |
| | L90/L70/L50/L30 • • • • • • • • • | L90/L70/L50/L30 | L90/L70/L50/L30 L90/L70/L50/L30 L90/L70/L50/L30 L90/L70/L50/L30 |

life is on

Since 1947, Phonak is dedicated to preserving life quality by opening new acoustic worlds. Already back then, in the days of our foundation, our company was driven by a formative conviction: We believe that well-hearing equates to well-being and thus is essential for living life to the fullest. In fact, the sense of hearing is directly linked to social, emotional, cognitive and physical well-being. Today as in future, we thrive to offer the broadest portfolio of innovative hearing solutions. And, together with our hearing care professionals, we keep on focusing on what matters most: improving speech understanding, changing people's lives and having a positive effect on society as a whole.

www.phonak.com



027-0667-02/V5-00/2023-10/na © 2022-2023 Sonova AG All rights reserved 7 "61 :





