

A Sonova brand

# Phonak Naída<sup>™</sup> L •

**Product information** 

Phonak Naída Lumity is the comprehensive BTE portfolio for mild to profound hearing losses.

۲

Powered by Phonak SmartSpeech<sup>™</sup> Technology, Naída L hearing aids are the choice for clients who need powerful solutions on our most advanced platform Phonak Lumity.



۲

# **Product description**

|   |                 |                                     |                                 |                |  |                |   | r                         |
|---|-----------------|-------------------------------------|---------------------------------|----------------|--|----------------|---|---------------------------|
|   |                 | Naída L-                            | a L-UP<br>-UP Trial<br>/L50/L30 |                | Naída L–SP<br>Naída L–SP Tria<br>L90/L70/L50/L30 | I              | Naída<br>Naída L-<br>L90/L70/   | PR Trial                  |
| Battery size                              |                 | 67                                  | 75                              |                | 13   |                | built-in re   | chargeable                |
| Telecoil                                  |                 | •                                   | •                               |                | •  |                |   |                           |
| Compatibility with CROS L                 |                 |                                     |                                 |                |  |                |   | •                         |
| Bluetooth®                                |                 | •                                   | •                               |                | •  |                |   | •                         |
| Hydrophobic coating                       |                 | •                                   | •                               |                | •  |                |   | •                         |
| IP rating                                 |                 | IPE                                 | 58 <sup>1</sup>                 |                | IP681  |                | IP  | 68 <sup>1</sup>           |
| Dimensions                                | L x W x D       | 42.6 x 18.8<br>(1.68 x 0.7          |                                 |                | 0.0 x 16.9 x 8.5 m<br>1.57 x 0.67 x 0.33         |                |   | 4 x 8.5 mm<br>64 x 0.33") |
|   | Weight          | 4.60 g /                            | 0.162 oz                        |                | 4.40 g / 0.155 oz                                |                | 3.68 g /  | 0.130 oz                  |
| Charging times <sup>2</sup>               | 0% to 100%      |                                     |                                 |                | 3 h  |                | h   |                           |
|   | 0% to 80%       |                                     |                                 |                |  |                | 1.  | 5 h                       |
|   | 30 min. fitting |                                     |                                 |                |  |                | 10  | min.                      |
|   |                 | HE11                                | HE11 680                        | HE11           | HE11 680   | SlimTube 4.0   | HE11 680  | SlimTube 4.0              |
| Max. Power Output (dB SPL)                | 2 cc coupler    | 141                                 | 134                             | 139            | 133  | 135            | 130   | 129                       |
| Max. gain (dB)                            | 2 cc coupler    | 84                                  | 78                              | 81             | 75   | 70             | 68  | 69                        |
| Frequency range (Hz)                      |                 | < 100 - > 4700                      | < 100 - > 4700                  | < 100 - > 4900 | < 100 - > 5700                                   | < 100 - > 7100 | < 100 - > 5700  | < 100 - > 710             |
| Fitting range<br>SlimTube 4.0<br>HE11 680 |                 | Severe to profou                    |                                 | Mild to        | 250 500 1k 2k<br>severe hearing lu               |                | dB HL<br>0<br>10<br>20<br>30<br>40<br>50<br>60<br>90<br>90<br>100<br>110<br>125<br>250<br>500<br>Mild to modera |                           |
|   |                 | loss, all audiome<br>configurations |                                 |                | netric configurati                               |                | hearing loss, a configurations  | ll audiometr              |

#### Housing colors

۲



1 IP68 indicates that the hearing aid is water and dust resistant. It survived continuous immersion in 1 meter of fresh water for 60 minutes and 8 hours in a dust chamber as per the IEC60529 standard. 2 Actual charging time depends on the remaining battery life and may be affected by temperature conditions.

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Sonova AG is under license.

۲

SmartSpeech Technology

## Performance levels

| AutoSense OS™ 5.0                   | Premium<br>L90 | Advanced | Standard<br>L50 | Essential |
|-------------------------------------|----------------|----------|-----------------|-----------|
| Speech in Loud Noise                | •              |          |                 |           |
| Speech in Car                       | •              |          |                 |           |
| Comfort in Echo                     | •              |          |                 |           |
| Music                               | •              | •        |                 |           |
| Comfort in Noise                    | •              | •        | •               |           |
| Speech in Noise                     | •              | •        | •               | •         |
| Calm Situation                      | •              | •        | •               | •         |
| Media speech + mic                  | •              | •        | •               | •         |
| Media music + mic                   | •              | •        | •               | •         |
| Additional programs                 |                |          |                 |           |
| Max. additional programs            | 4              | 4        | 4               | 4         |
| Comfort in Echo                     | •              |          |                 |           |
| Speech in Loud Noise                | •              | •        |                 |           |
| Speech in 360°                      | •              | •        |                 |           |
| Speech in Noise                     | •              | •        | •               | •         |
| Calm Situation                      | •              | •        | •               | •         |
| Comfort in Noise                    | •              | •        | •               | •         |
| Music                               | •              | •        | •               | •         |
| Acoustic phone                      | •              | •        | •               | •         |
| Custom program                      | •              | •        | •               | •         |
| Phone via T-coil ± mic <sup>1</sup> | •              | •        | •               | •         |
| Public T-coil ± mic <sup>1</sup>    | •              | •        | •               | •         |
| Streaming programs                  |                |          |                 |           |
| RogerDirect + mic                   | •              | •        | •               | •         |
| Phonak PartnerMic™ + mic            | •              | •        | •               | •         |
| Phone call + mic                    | •              | •        | •               | •         |

| Features                              | Premium<br>L90 | Advanced | Standard<br>L50 | Essentia<br>L30 |
|---------------------------------------|----------------|----------|-----------------|-----------------|
| SpeechSensor                          | •              |          |                 |                 |
| Speech Enhancer                       | •              |          |                 |                 |
| StereoZoom 2.0                        | •              | •        |                 |                 |
| Dynamic Noise<br>Cancellation         | •              | •        |                 |                 |
| Motion Sensor Hearing <sup>2</sup>    | •              | •        | •               |                 |
| RogerDirect™                          | •              | •        | •               | •               |
| EchoBlock                             | •              |          |                 |                 |
| Tap control <sup>2</sup>              |                |          |                 |                 |
| - Siri/Google Assistant               | •              | •        |                 |                 |
| - Pause/resume streaming              | •              | •        |                 |                 |
| - Accept/end phone call               | •              | •        |                 |                 |
| SoundRelax                            | •              | •        |                 |                 |
| DuoPhone                              | ٠              | •        | •               |                 |
| Real Ear Sound                        | •              | •        | •               |                 |
| UltraZoom                             | •              | •        | •               | •               |
| Roger <sup>™</sup> and Directional    | ٠              | •        | •               | •               |
| setting                               |                |          |                 |                 |
| Broadband Booster <sup>3</sup>        | ٠              | •        | •               | ٠               |
| Health functionalities <sup>2,4</sup> | ٠              | •        | •               | •               |
| WindBlock                             | •              | •        | •               | •               |
| User Preference Tuning                | •              | •        | •               | •               |
| Tinnitus Balance⁵                     | ٠              | •        | •               | ٠               |
| Auto Acclimatization                  | ٠              | •        | •               | ٠               |
| Environmental balance                 | ٠              | •        | •               | ٠               |
| SoundRecover2                         | ٠              | •        | •               | ٠               |
| WhistleBlock                          | •              | •        | •               | ٠               |
| NoiseBlock                            | ٠              | •        | •               | •               |
| QuickSync                             | ٠              | •        | •               | •               |
| AOV                                   | ٠              | •        | •               | •               |
| Fine tuning channels                  | 20             | 20       | 16              | 12              |

1 Not available for Phonak Naida L-PR 2 Available for Phonak Naida L-PR only 3 Available for Phonak Naida L-UP only 4 Available in combination with myPhonak 5 Not available for Phonak Naida L-UP

#### Fitting

۲

| 5                                       | Naída L-UP<br>Naída L-UP Trial<br>L90/L70/L50/L30 | Naída L–SP<br>Naída L–SP Trial<br>L90/L70/L50/L30 | Naída L–PR<br>Naída L–PR Trial<br>L90/L70/L50/L30 |
|---|---|---|---|
| Phonak Target                           | 9.0 or higher                                     | 9.1 or higher                                     | 9.0 or higher                                     |
| Noahlink Wireless / Noahlink Wireless 2 | •   | •   | ٠   |
| NOAHLink                                | •   | •   |   |
| HI-PRO, HI-PRO2                         | ٠   | •   |   |

#### Acoustic coupling

|                       |              |  | Naída L-UP<br>Naída L-UP Trial<br>L90/L70/L50/L30 | Naída L–SP<br>Naída L–SP Trial<br>L90/L70/L50/L30 | Naída L-PR<br>Naída L-PR Trial<br>L90/L70/L50/L30 |
|-----------------------|--------------|--|---|---|---|
| Sound outlet          | Hook         | Damped (HE11 680), transparent                                     | •   | •   | •   |
|                       | Hook         | Undamped (HE11), transparent                                       | •   | •   |   |
|                       | SlimTube 4.0 | Available in left and right in five different lengths (00,0,1,2,3) |   | •   | •   |
| Earpiece for SlimTube | Dome         | Cap dome   |   | •   | •   |
|                       |              | Open dome Available in three sizes (S, M, L)                       |   | •   | •   |
|                       |              | Vented dome Available in three sizes (S, M, L)                     |   | •   | •   |
|                       |              | Power dome Available in three sizes (S, M, L)                      |   | •   | •   |
|                       | SlimTip      | Acrylic  |   | •   | •   |
|                       |              | Silicone   |   | •   | •   |
| Earpiece for hook     | Earmold      |  | •   | •   | •   |

۲

#### Phonak Naída L Trial

۲

The Phonak Naída L Trial hearing aids can be quickly set to the required performance level in order to suit your recommendation. This provides you the ability to fit your client with the optimal hearing solution already at the first appointment or to provide a replacement when the client's hearing aid is in for repair. The Naída L Trial devices also include a pre-installed Roger receiver for easy demonstration and trial of any Roger microphone.

۲

#### Phonak Naída L-PR charging options

#### Phonak Charger Combi BTE / Phonak Charger Combi BTE 2

Naída L-PR has all the Lumity features you love as well as the benefit of rechargeability. Clients can enjoy a full day of hearing including streaming\*.

\* Expected battery life of 16 hours, including 4 hours of BT classic streaming and 4 hours of TV Connector streaming.



#### Phonak Naída L Bluetooth<sup>®</sup> versions

Direct calls/audio streaming

Bluetooth 4.2 wireless technology and most older Bluetooth phones

۲

#### Wireless communication portfolio

| Naída L-UP<br>Naída L-UP Trial | Naída L–SP<br>Naída L–SP Trial | Naída L-PR<br>Naída L-PR Trial                                      |
|--------------------------------|--------------------------------|---|
| L90/L70/L50/L30                | L90/L/0/L50/L30                | L90/L70/L50/L30   |
|                                |                                |   |
| •                              | •                              | •   |
| •                              | •                              | •   |
| •                              | •                              | •   |
|                                |                                |   |
| •                              | •                              | ٠   |
|                                |                                |   |
| •                              | •                              | ٠   |
| •                              | •                              | •   |
|                                |                                | Naída L-UP Trial Naída L-SP Trial   L90/L70/L50/L30 L90/L70/L50/L30 |

For more information please visit www.phonak.com/naida-lumity

For information on Roger microphones please visit www.phonak.com/roger

For more information on myPhonak and myPhonak Junior please visit www.phonak.com/apps

۲

### life is on

Since 1947, Phonak is dedicated to preserving life quality by opening new acoustic worlds. Already back then, in the days of our foundation, our company was driven by a formative conviction: We believe that well-hearing equates to well-being and thus is essential for living life to the fullest. In fact, the sense of hearing is directly linked to social, emotional, cognitive and physical well-being. Today as in future, we thrive to offer the broadest portfolio of innovative hearing solutions. And, together with our hearing care professionals, we keep on focusing on what matters most: improving speech understanding, changing people's lives and having a positive effect on society as a whole.

www.phonak.com

۲



۲

027-0699-02/V3.00/2024-02/na © 2024 Sonova AG All rights reserved





Sonova AG · Laubisrütistrasse 28 CH-8712 Stäfa · Switzerland



